



GENSET MG 23 US-Y - SINGLE-PHASE/THREE-PHASE GENERATOR 22 KVA

Reference: MG 23 US-Y

GENSET MG 23 US-Y

The GENSET MG 23 US-Y is a single-phase/three-phase 22 KVA diesel generator with electric start. Thanks to its compact size and its very low weight, the GENSET MG 23 US-Y is a light and easy to transport generator. The GENSET MG 23 US-Y also has a low fuel consumption: only 3.5 Lt/h at 75% of the load. The GENSET MG 23 US-Y generator set, thanks to the high quality and efficiency of its components, is ideal for various types of work: from small hobby jobs to large construction sites.

Images and technical data are not binding.

Technical Sheet

Phase	Single phase / Three phase
Maximum power single phase (KW)	5.84
Maximum power single phase (KVA)	7.3
Maximum power three phase (KW)	17.6
Continuous power three phase (KW)	15.84
Maximum power three phase (KVA)	22
Continuous power three phase (KVA)	19.8
Fuel	Diesel
Frequency (Hz)	50
Voltage (V)	230 / 400
Sockets configuration	1 x 400V 16A CEE - 1 x 400V 32A CEE - 3 x 230V 16A CEE
Engine	Yanmar 4TNV88, 4 stroke
Emissions Regulations	Stage 5
Engine rpm (rpm)	1500
Starting system	Electric
Engine capacity (cm ³)	2190

Number cylinders	4
Cooling	Water
Alternator	Synchronous
Protection degree	IP23
Motor insulation class	H
Fuel tank capacity (L)	70
Consumption (L/h)	3.5
Running time (h)	20
Acoustic power	92 dB(A)
Acoustic pressure	67 dB(A) at 7 m
Length (mm)	1645
Width (mm)	755
Height (mm)	1212
Dry weight (Kg)	610
Silenced	Yes
Super silenced	Yes
Product type	Generator
ATS Switch device	Optional ATS
Voltage regulator	Compound / AVR (optional)
Engine manufacturer	Yanmar