



## AGROWATT AWB 4-32X PTO Generator Single Phase/ Three Phase 32.4 kVA AVR

Reference: 113904

- For outdoor applications (field and home), in case of blackouts and in areas not served by the power grid
- Supplied with multiplier kit and protection, support with 3-point attachment (patented design), electrical panel with multifunction digital display for real-time data reading (voltmeter, frequency meter, ammeter, hour meter)
- Durability over time and maximum protection (thermal-magnetic and differential)
- Warranty 24 months
- Easy packaging and subsequent storage

Control Panel with:

- 1 CEE 400V (3P+N+E) 63A
- 1 CEE 230V (2P+E) 32A
- 1 schuko
- single phase thermal protection
- 4-pole magnetothermic switch + earth leakage breaker (Id=0,03A) + 2 pole magnetothermic switch + IP65 cover
- voltmeter + frequencymeter + ammeter + hour counter (digital measurement instrument)

Non-binding images and technical data.

### Technical Sheet

| Phase                            | Single phase / Three phase |
|----------------------------------|----------------------------|
| Maximum power single phase (KVA) | 13                         |
| Maximum power three phase (KVA)  | 32.5                       |
| Frequency (Hz)                   | 50                         |
| Voltage (V)                      | 230 / 400                  |
| Sockets configuration            |                            |
| Engine rpm (rpm)                 | 1500                       |
| Poles                            | 4                          |
| Protection degree                | IP44                       |
| PTO speed (round/min)            | 430                        |
| Minimum tractor output (HP)      | 95                         |

---

|                    |         |
|--------------------|---------|
| Transmission ratio | 1 : 3.5 |
| Length (mm)        | 1135    |
| Width (mm)         |         |
| Height (mm)        | 915     |
| Dry weight (Kg)    | 248     |
| Brushes            | No      |
| Voltage regulator  | AVR     |

---