



## CGM C11000

Reference: CGM C11000

### CGM C11000 single-phase 10 KVA generator

Generator CGM C11000 single-phase 10 KVA generator with Briggs & Stratton engine powered by STAGE V gasoline at 3000 rpm, compact and easy to use, mounted on a fixed base with rubber vibration dampers.

The CGM C11000 generator is composed of a Made in Italy alternator by Linz or NSM, self-excited without brushes and with AVR voltage regulator. The CGM C11000 generator set is equipped with a manual recoil starter, but it is also available in the version with electric start and with a low fuel consumption, in fact it consumes only 3.8 liters/hour at 75% of the load. This generating set C11000 is perfect for outdoor use as for example for hobby use.

The CGM C11000 generating is part of the CLASSIC series and is easily adaptable to various uses such as homes, mobile facilities, camping, hobbies, construction sites, etc.. The C11000 generator set at 3000 rpm is suitable for emergency use only. It is not recommended to be used for more than 6 hours continuously and for more than 500 hours per year.

#### Technical features of CGM C11000 generator:

Phase type: Single phase  
Maximum power: 9.9 KW  
Continuous use power: 9 KW  
Maximum power: 11 KVA  
Continuous use power: 10 KVA  
Fuel: Gasoline  
Voltage: 230 V  
Frequency: 50 Hz  
Motor: BRIGGS & STRATTON 16HP  
Motor RPM: 3000 RPM  
Start: Manual  
Voltage regulator system: AVR  
Consumption: 3.8 Lt/h at 75% load  
Tank capacity: 8.5 Lt  
Autonomy: 2.2 h at 75% load  
Length: 910 mm  
Width: 580 mm  
Height: 640 mm  
Weight: 97 Kg

Discover the full range reserved for [Ground generators](#) of CGM or other top brands by browsing our catalog to find the one that best suits your needs.

Images and technical data are not binding.

## Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	9.9
Continuous power single phase (KW)	9
Maximum power single phase (KVA)	11
Continuous power single phase (KVA)	10
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230
Sockets configuration	
Engine	Briggs&Stratton
Emissions Regulations	Stage 5
Engine rpm (rpm)	3000
Starting system	Manuale
Engine capacity (cm <sup>3</sup> )	480
Number cylinders	2
Alternator	Made in Italy
Poles	2
Fuel tank capacity (L)	
Consumption (L/h)	3.8
Running time (h)	2.2
Length (mm)	910
Width (mm)	580
Height (mm)	640
Dry weight (Kg)	97
Silenced	No
Super silenced	No
Product type	Generator
ATS Switch device	No ATS
Voltage regulator	AVR
Engine manufacturer	Briggs&Stratton