



## TECNOGEN H1500TSS AVR

Reference: H1500TSS NOLEGGIO

### GENERATOR RENTAL SET 13KVA AVR SET - TECNOGEN H1500TSS SINGLE-PHASE / THREE-PHASE POWER

Generator Rental 13KVA AVR - TECNOGEN H1500TSS singlephase / threephase generator, equipped with a Honda GX690 gasoline engine, capable of delivering a maximum three-phase power of 13KVA **complete with AVR voltage regulator**

Generator Rental 13KVA AVR TECNOGEN H1500TSS is super silenced, with electric start, with a power of 4,3KVA singlephase and 13 KVA threephase maximum.

#### RENTAL SERVICE TURIN AND ITALY

Generator 13KVA AVR TECNOGEN H1500TSS has never been easier: choose the product you want to rent and [FILL OUT THE FORM](#).

Our specialized staff will answer you immediately with the most suitable offer for you!

The equipment available for rental can be shipped throughout Italy and is always ready for action: our team of technicians will always keep it in perfect working condition.

It is advisable to book in advance for the rental of large quantities of machines: this is especially important in conjunction with trade fairs or events, where many people will use the rental service.

Generator Rental 13KVA AVR TECNOGEN H1500TSS is equipped with the latest generation Honda engine, running on gasoline, characterized by high quality components and a very low sound level.

This Rental generating set is also available with an automatic panel ATS able to perceive the absence of tension from the electric net and to send the ignition signal to the generating set, switching the load supplied by the electric net.

#### Voltage Regulator AVR

The Generator Rental 13KVA AVR TECNOGEN H1500TSS is equipped with a voltage regulator. The AVR is a device that allows to **keep the output more constant and less dependent on the load**. Thanks to this card there are fewer drops or spikes in current and this makes it safer to use the various devices connected, improving performance and durability.

TECHNICAL FEATURES GENERATION SET TECNOGEN H1500TSS:

Phase Type: Singlephase / Threephase  
Continuous Singlephase Output: 3.5 KVA / 2.7 KW  
Maximum Singlephase Output: 3.8 KVA / 3 KW

Continuous Threephase Output: 12 KVA / 9.6 KW  
 Maximum Threephase Output: 13 KVA / 10.4 KW  
 Power Factor cos fi?: 0.8  
 VAC voltage: 230 / 400 V  
 Frequency (Hz): 50  
 Voltage regulator: AVR  
 Start-up switch: manual  
 Motor: Honda GX690  
 RPM: 3000  
 Power supply: Gasoline  
 Tank capacity: 20 l  
 Consumption: 7 l/h @ 75 % of load  
 Run time: 2.85 h  
 Acoustic pressure: 88 @ 7m  
 Length: 1070 mm  
 Width: 560 mm  
 Height: 930 mm  
 Net weight: 210 Kg

Are you looking to rental a generator with different technical characteristics? [Here](#) you can find our entire rental fleet where you can find the perfect generator for you.

Available for Turin and all of Italy.

The image is purely indicative.

## Technical Sheet

Phase	Single phase / Three phase
Maximum power single phase (KW)	3
Continuous power single phase (KW)	2.7
Maximum power single phase (KVA)	3.8
Continuous power single phase (KVA)	3.5
Maximum power three phase (KW)	10.4
Continuous power three phase (KW)	9.6
Maximum power three phase (KVA)	13
Continuous power three phase (KVA)	12
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230 / 400
Engine	HONDA GC160
Engine rpm (rpm)	3000
Speed governor	Electronic
Starting system	Electric
Engine capacity (cm <sup>3</sup> )	688
Number cylinders	2

Cooling	Air
Fuel tank capacity (L)	20
Consumption (L/h)	7
Running time (h)	2.8
Acoustic power	88 dB(A)
Length (mm)	1070
Width (mm)	560
Height (mm)	930
Dry weight (Kg)	210
Silenced	Yes
Super silenced	Yes
ATS Switch device	Optional ATS
Voltage regulator	AVR
Engine manufacturer	Honda