



GENMAC Combiplus RG9100KEO GENERATOR 10,2KVA

Reference:

GENMAC Combiplus RG9100KEO SINGLE-PHASE GENERATOR 10,2KVA

The generator Genmac Combiplus RG9100KEO single phase is equipped with a Kohler Diesel powered engine capable of delivering a power of 10,2KVA with capacitor voltage regulator (AVR optional).

Genmac Diesel professional high quality diesel generators, are equipped with a Kohler KD440 engine, which generates a continuous power of 9,8kva in only 3000 rpm and a maximum limited power (L.T.P.) of 10,2KVA . The engine is cooled by a fan, favoring and allowing a prolonged use of the generator without running the risk of overheating the mechanical parts that compose it.

Genmac professional diesel generators are highly reliable machines, built with quality components to be used in the professional field, where reliability is fundamental.

The Kohler engine is oversized compared to generators of the same power normally available on the market.

This feature is fundamental to ensure a high reliability of the generator, reduces its effort and increases its life span by lowering the noise level.

The 10,2KVA generator is equipped with a capacitor voltage regulator, on request it can be supplied with the AVR regulator.

AVR Voltage Regulator

All models in the Genmac Combipro series are available with optional AVR voltage regulator. The AVR is a device that allows to **maintain the output more constant and less load-dependent**. Thanks to this card you have fewer drops or current peaks and this makes it safer to use the various devices connected, improving their performance and durability.

The model equipped with AVR card is highly recommended, as it guarantees a significant improvement in the stability of the output; this feature makes the generators particularly suitable with common use machines with reactive load such as refrigerators, freezers, air conditioners and garden machines. Thanks to the AVR you can enjoy greater stability and thus increase the life of your devices.

TECHNICAL FEATURES OF GENERATOR GENMAC Combiplus RG9100KEO 10,2KVA

Voltage regulator : capacitor (AVR Optional)

Power supply: Diesel

Starting: Electric

Single-phase

Continuous output: 8,8KW

Continuous output: 9,8KVA

Maximum Output: 9,8KW

Maximum output: 10,2KVA
Voltage: 230V
Frequency: 50 Hz
3000 revolutions per minute
Tank: 19 Lt.
Autonomy @ 75%: 7,6 h fixed revolutions
Starting: Manual
Length (mm): 870
Width (mm): 620
Height (mm): 690
Dry weight (Kg): 163

If you are looking for another product then you can see on [our catalog other](#).

Images and technical data are not binding.

Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	9.8
Continuous power single phase (KW)	8.8
Maximum power single phase (KVA)	10.2
Continuous power single phase (KVA)	
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230
Engine	Kohler KD 425/2
Engine rpm (rpm)	3000
Starting system	Elettrico
Cooling	Air
Poles	2
Fuel tank capacity (L)	19
Running time (h)	7.6
Length (mm)	860
Width (mm)	620
Height (mm)	690
Dry weight (Kg)	163
ATS Switch device	Optional ATS
Voltage regulator	AVR (optional)
Engine manufacturer	Kohler