

GENMAC DAILY G6500YS GENERATOR 6,9KVA



Reference:

GENMAC DAILY G6500YS THREE-PHASE GENERATOR 6,9KVA

The Genmac Daily G6500YS three-phase generator is equipped with a diesel-powered Yanmar engine capable of delivering 6.9KVA with capacitor voltage regulator (AVR optional).

High quality professional silenced three-phase diesel power generator, Genmac Daily G6500YS with 6.9KVA power output. The Genmac Daily G6500YS diesel power generator is equipped with an oversized Yanmar air-cooled engine.

Genmac Daily G6500YS professional diesel generators, are highly reliable machines, built with quality components for use in the professional field, where reliability is paramount.

This feature is essential to ensure high reliability of the Genmac Daily G6500YS, reduces the strain on it and **increases its lifespan by lowering the noise level.**

All **Yanmar engines** are built using the **best materials**, the **most innovative techniques** and the **most advanced methods of quality control.**

Each engine is thoroughly tested to ensure that it is in perfect working order before delivery. Yanmar's service department is always available to assist you if you need it.

The 6,9KVA Genmac Daily G6500YS is equipped with a capacitor voltage regulator, on request it can be supplied with the AVR regulator.

Voltage Regulator AVR

All models in the Genmac series are available with an optional AVR voltage regulator. The AVR is a device that allows you to **keep the output more constant and less dependent on the load.** Thanks to this card there are fewer drops or spikes in current and this makes it safer to use the various devices connected, improving performance and durability.

The model equipped with AVR card is highly recommended, as it ensures a significant improvement in the stability of the output; this feature makes the generators particularly suitable with commonly used machines with reactive load such as refrigerators, freezers, air conditioners and garden machines. Thanks to the AVR you will enjoy greater stability and therefore an increase in the life of your devices.

TECHNICAL FEATURES GENMAC Daily G6500YS 6.9KVA

Voltage regulator : capacitor (AVR Optional)
Power supply: Diesel
Firing: Electric
Phase type: Singlephase/ Threephase
Singlephase continuous power: 1.9KVA / 1.5KW

Maximum singlephase power: 2.3KVA / 1.8KW
 ThreePhase Continuous Power: 5.6KVA / 4.5KW
 ThreePhase Maximum Power: 6.9KVA / 5.6KW
 Motor: Yanmar L100
 Socket Frame: 1 x 16A 230V / 1 x 32A 230V / 1 x 16A 400V
 Voltage: 230 / 400 V
 Frequency: 50 Hz
 3000 revolutions per minute
 Tank capacity: 19 l
 Autonomy @ 75%: 15 h fixed revolutions
 Acoustic pressure @7m: 67 dBa
 Length (mm): 1030
 Width (mm): 620
 Height (mm): 804
 Dry weight (Kg): 203

If you are looking for another product then you can see on our catalog other [overland generators](#).

Images and technical data are not binding.

Technical Sheet

Phase	Single phase / Three phase
Maximum power single phase (KW)	1.8
Continuous power single phase (KW)	1.5
Maximum power single phase (KVA)	2.3
Continuous power single phase (KVA)	1.9
Maximum power three phase (KW)	5.5
Continuous power three phase (KW)	4.5
Maximum power three phase (KVA)	6.9
Continuous power three phase (KVA)	5.6
Fuel	Diesel
Frequency (Hz)	50
Voltage (V)	230 / 400
Sockets configuration	
Engine	Yanmar L100, 4 stroke
Engine rpm (rpm)	3000
Starting system	Elettrico
Cooling	Air
Poles	2
Fuel tank capacity (L)	19

Running time (h)

Acoustic pressure

67 dB(A) at 7 m

Length (mm)

Width (mm)

620

Height (mm)

Dry weight (Kg)

203

Silenced

Yes

Super silenced

Yes

ATS Switch device

Optional ATS

Voltage regulator

Capacitor / AVR (optional)

Engine manufacturer

Yanmar