



GENMAC Daily RG5000YS-M5 GENERATOR 6,1KVA

Reference:

GENMAC Daily RG5000YS-M5 SINGLE-PHASE GENERATOR 6,1KVA

The Genmac Daily RG5000YS-M5 single-phase generator is equipped with a Yanmar L100 Stage V Diesel-powered engine capable of delivering 6,1KVA with capacitor voltage regulator (AVR optional).

The Genmac Daily RG5000YS-M5 professional generators are highly reliable machines, built with quality components for use in the professional field, where reliability is paramount.

The **Stage V** engine allows the Genmac Daily RG5000YS-M5 **even for mobile use**, such as for road construction sites and rental services. The generator is suitable for applications in various contexts such as: hospitals, industries, shopping malls, hotels, airports, banks, universities, stadiums, offices, etc.

This feature is essential to ensure high reliability of the Genmac Daily RG5000YS-M5, reduces the strain on it and **increases its lifespan by lowering the noise level**.

All **Yanmar engines** are manufactured using the **best materials**, the **most innovative techniques** and the **most advanced methods of quality control**.

Each engine is thoroughly tested to ensure that it is in perfect working order before delivery. Yanmar's service department is always available to assist you if you need it.

The Genmac Daily RG5000YS-M5 is equipped with a capacitor voltage regulator, on request it can be supplied with AVR regulator.

Voltage Regulator AVR

All models in the Genmac series are available with an optional AVR voltage regulator. The AVR is a device that allows you to **keep the output more constant and less dependent on the load**. Thanks to this card there are fewer drops or spikes in current and this makes it safer to use the various devices connected, improving performance and durability.

The model equipped with AVR card is highly recommended, as it ensures a significant improvement in the stability of the output; this feature makes the generators particularly suitable with commonly used machines with reactive load such as refrigerators, freezers, air conditioners and garden machines. Thanks to the AVR you will enjoy greater stability and therefore an increase in the life of your devices.

TECHNICAL FEATURES GENMAC Daily RG5000YS-M5 6.1KVA

Voltage regulator : capacitor (AVR Optional)
Power supply: Diesel
Firing: Electric
Phase type. Single Phase
Continuous Power: 5.0KVA / 4.5KW

Maximum Power: 6.1KVA / 5.5KW
 Engine: Yanmar L100
 Emissions Standard: Stage V
 Socket panel: 1 x 16A 230V - 2 x 32A 230V
 Voltage: 230V
 Frequency: 50 Hz
 3000 rpm
 Sound pressure @7m : 68 dBa
 Tank capacity: 19
 Autonomy @ 75%: 15 h fixed rpm
 Length (mm): 1030
 Width (mm): 620
 Height (mm): 804
 Dry weight (Kg): 200

If you are looking for another product then you can see on our catalog other [ground generators](#).

Images and technical data are not binding.

Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	5.5
Continuous power single phase (KW)	4.5
Maximum power single phase (KVA)	6.1
Continuous power single phase (KVA)	5
Fuel	Diesel
Frequency (Hz)	50
Voltage (V)	230
Sockets configuration	
Engine	Yanmar L100, 4 stroke
Emissions Regulations	Stage 5
Engine rpm (rpm)	3000
Starting system	Elettrico
Cooling	Air
Poles	2
Fuel tank capacity (L)	19
Running time (h)	
Acoustic pressure	68 dB(A) at 7 m
Length (mm)	
Width (mm)	620
Height (mm)	

Dry weight (Kg)	200
Silenced	Yes
Super silenced	Yes
Voltage regulator	AVR (optional)
Engine manufacturer	Yanmar
