



## MASE EA 40 GH

Reference: 003269

### MASE EA 40 GH SINGLE-PHASE GENERATOR 3.85KW

MASE EA 40 GH is a single-phase generator equipped with a Honda GX200 gasoline engine, capable of delivering a maximum power of 3.85KW.

The MASE EA 40 GH single-phase generator provides reliable power for home, work and leisure environments, safely powering home appliances and other electronic devices.

The generator is as easy to install and operate as it is to start and stop thanks to clear, intuitive controls. MASE EA 40 GH is equipped with a Honda GX200 gasoline engine. They are very reliable engines that provide efficient combustion and **low fuel consumption**. The engines with which the MASE EA 40 GH are equipped are also equipped with a protection system that causes the engine to stop if the oil level is too low.

MASE EA 40 GH is a stationary use machine, before commissioning you must first secure the generator firmly to the ground. MASE EA 40 GH power generators are equipped with **3.1liter** reservoir with a large cap that is convenient to unscrew even with work gloves

MASE EA 40 GH has an all-steel structure and a large metal tank. The generator guarantees an efficient and silent operation thanks to the Honda GX200 engine which allows to deliver a maximum power of 3,85KW.

#### TECHNICAL CHARACTERISTICS MASE EA 40 GH

Maximum power Single-phase: 3.85 KW  
Fuel: Gasoline  
Voltage: 230 V  
Frequency: 50 Hz  
Engine: Honda GX200  
Engine displacement: 196 cm<sup>3</sup>  
Cooling: Air  
Starting: Manual  
Tank capacity: 3.1 l  
Consumption: 1.5 Lt/h at 75% load  
Acoustic power: 98 dB (73 dB at 7 m)  
Protection class: IP 23  
Length: 610 mm  
Width: 360 mm  
Height: 410 mm  
Weight: 38 Kg

Are you looking for a power generator with different characteristics? [Here](#) you can find the full range of products MASE or other

brands specializing in the field

Images and technical data are not binding and may be subject to revision by the supplier.

## Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	3.85
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230
Sockets configuration	2 x 230V SCHUKO
Engine	Honda GX200, 4 stroke
Engine rpm (rpm)	3000
Starting system	Manual
Engine capacity (cm <sup>3</sup> )	196
Number cylinders	1
Cooling	Air
Alternator	Synchronous
Fuel tank capacity (L)	3.1
Consumption (L/h)	1.5 al 75% del carico
Acoustic power	98 dB(A)
Acoustic pressure	73 dB(A) at 7 m
Length (mm)	610
Width (mm)	360
Height (mm)	410
Dry weight (Kg)	38
Silenced	No
Super silenced	No
ATS Switch device	No ATS
Voltage regulator	No
Engine manufacturer	Honda