



CGM CS13000T THREE-PHASE GENERATOR STAGE V 13KVA

Reference: CS13000T

CGM CS13000T THREE-PHASE STAGE V 13KVA GENERATOR

CGM CS13000T Three-phase generator 13KVA with BRIGGS & STRATTON engine powered by STAGE V gasoline at 3000 rpm, compact and easy to use.

The CGM CS13000T generator consists of an NSM Made in Italy, self-excited brushless alternator with **AVR** voltage regulator. The generator is equipped with electric start with battery that allows a practical and fast use even when cold. The CGM CS13000T has a low fuel consumption, in fact it consumes only 4,9 liters/hour at 75% of the load.

The CGM CS13000T is part of the QUIET series because thanks to the hood has low noise emissions and is supersilenced. This generator is 3000 RPM, with BRIGGS & STRATTON diesel engine with electric start with key and battery.

Technical features of the CGM CS13000T:

Phase Type: Three Phase
Maximum Power: 11,4KW
Continuous Power: 10,4KW
Maximum Power: 14,3KVA
Continuous Power: 13KVA
Fuel: Gasoline
Voltage: 400 V
Frequency: 50 Hz
Engine: BRIGGS & STRATTON 21HP
Cooling: Air
Number of Cylinders: 2
Emission Standard: Stage V
Engine RPM: 3000 rpm
Start: Electric
Alternator: NSM made in Italy
Tension regulator system: AVR
Consumption: 4.9 Lt/h at 75% load
Tank capacity: 50 Lt
Autonomy: 10.2 h at 75% load
Length: 1100 mm
Width: 600 mm
Height: 830 mm
Weight: 224 Kg
Super-silenced

Discover the full range of [current generator](#) of CGM on our catalog to find the one that best suits your needs.

Pictures and technical data not binding.

Technical Sheet

Phase	Three phase
Maximum power three phase (KW)	11.4
Continuous power three phase (KW)	10.4
Maximum power three phase (KVA)	14.3
Continuous power three phase (KVA)	13
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	400
Sockets configuration	n.1 presa CEE 16A 3P 230V, n.1 presa CEE 32A 3P 230V, n. 1 presa CEE 32A 5P 400V
Engine	BRIGGS & STRATTON 21HP
Emissions Regulations	Stage 5
Engine rpm (rpm)	3000
Starting system	Elettrico
Engine capacity (cm ³)	627
Number cylinders	2
Cooling	Air
Alternator	NSM, made in Italy
Fuel tank capacity (L)	50
Consumption (L/h)	
Running time (h)	10,2 al 75% del carico
Length (mm)	
Width (mm)	600
Height (mm)	830
Dry weight (Kg)	224
Silenced	Yes
Super silenced	Yes
Product type	Generator

Voltage regulator

AVR

Engine manufacturer

Briggs&Stratton
