



LINZ PRO18L F/4 Three-phase alternator 4 poles 60 kVA 60 Hz AVR

Reference: PRO18L F/4 60 Hz

The alternators of **PRO** series are three-phase brushless 4 poles with electronic regulation (AVR) with single-phase sensing (PRO18-PRO22) and three-phase sensing (PRO28-PRO35-PRO40).

CHARACTERISTICS

- Compact and mechanically resistant
- Excellent wave form
- Minimum maintenance
- High efficiency
- Type: Three-phase alternators
- Poles: 4
- Phases: Three-phase
- Regulation: AVR
- Application: INDUSTRIAL, COGENERATION

Technical Sheet

Phase	Three phase
Continuous power three phase (KVA)	60
Frequency (Hz)	60
Voltage (V)	230 / 400
Engine rpm (rpm)	1800
Alternator	Synchronous
Poles	4
Three-phase power (KVA)	50
Protection degree	IP23

Motor insulation class	H
Length (mm)	642
Width (mm)	362
Height (mm)	458
Brushes	No
PMG	No
Type of alternator	Constant Speed
Voltage regulator	AVR
Weight (Kg)	236.5