

GENERATOR RENTAL 800 KVA



Reference: GE 800 KVA PERKINS NOLEGGIO

GENERATOR RENTAL 800 KVA - PERKINS SINGLE PHASE/THREE PHASE GENERATOR

Generator Rental 800 KVA - PERKINS singlephase / threephase generating set equipped with PERKINS 3012TAG3A Diesel engine capable of delivering a maximum power of 800KVA, complete with **voltage regulator**.

Generator Rental 800KVA PERKINS is compact and easy to use, equipped with enclosure with sound-absorbing panels that greatly lower noise emissions and makes it **supersilenced**. The Generator 800 KVA generator set is composed of a MARELLI alternator and a voltage regulator. Generator Rental 800 KVA set is equipped with electric and with a low fuel consumption, in fact it consumes only 127 liters/hour at 75% of the load for an autonomy of up to 7.87 hours of operation. GE 800KVA is equipped with electric start or automatic start through ATS panel, which allows the automatic start in case of blackout.

ATS Authomatic Transfer Switch

Generator Rental 800 KVA is prepared for the use of the ATS Authomatic Transfer Switch. Thanks to which you will no longer have to worry about black-outs because if the mains fails, this panel is able to automatically start the Generator Rental 800 KVA and allow you to continue your business without losing your work data.

RENTAL SERVICE TURIN AND ITALY

Rental a generator has never been so easy: choose the product you want to rent and [FILL OUT THE FORM](#).

Our specialized staff will respond immediately with the offer that best suits you!

The equipment available for rental can be shipped throughout Italy and is always ready for action: our team of technicians will always keep it in perfect working condition.

It is advisable to book in advance for the rental of large quantities of machines: this is especially important in conjunction with trade fairs or events, where many people will use the rental service.

TECHNICAL CHARACTERISTICS GE 800KVA

Phase Type: SinglePhase / ThreePhase
Maximum SinglePhase Power: 266 KVA / 213KW
Maximum ThreePhase Power: 800 KVA / 640KW
Power Factor cos fi?: 0.8
VAC voltage: 230 / 400 V
Frequency (Hz): 50
Voltage regulator: Yes
Startup switch: Manual / Automatic

Motor: PERKINS 3012TAG3A
RPM: 1500
Power supply: Diesel
Tank capacity: 1000 l
Consumption @ 75 % of load: 127 l/h
Autonomy @ 75 % of load: 7.87 h
Acoustic pressure: 75 dB(A) @ 7m
Length: 5500 mm
Width: 2100 mm
Height: 2500 mm
Net weight: 8200 Kg

Are you looking to rent a generator set with different technical characteristics? [Here](#) you can find our entire rental fleet in which you can find the perfect generator for you.

Available for Turin and all of Italy.

The images are purely indicative.

Sed ligula felis, varius ac justo vitae, posuere dictum tortor. Duis euismod felis vel egestas malesuada. Etiam facilisis elit sit amet neque pretium, nec pretium ligula pellentesque. Vivamus in blandit nulla, id mollis orci. Duis tincidunt, erat sed pellentesque tempus, lectus sapien euismod diam, et euismod velit metus at metus. Nulla non pharetra lacus. Morbi tincidunt tincidunt est, nec auctor mi pretium eget. Sed venenatis dolor est, ac efficitur dolor rutrum a. Nunc tempus egestas erat, congue tristique dolor accumsan ac. Mauris eget cursus massa. Maecenas dignissim augue tortor, in commodo nunc pharetra eget.

...

Technical Sheet

Phase	Single phase / Three phase
Maximum power single phase (KW)	213
Maximum power single phase (KVA)	266
Maximum power three phase (KW)	640
Maximum power three phase (KVA)	800
Fuel	Diesel
Frequency (Hz)	50 / 60
Voltage (V)	230 / 400
Sockets configuration	Morsettiera
Engine	PERKINS 3012TAG3A
Emissions Regulations	Stationary Use
Engine rpm (rpm)	1500
Speed governor	Mechanical
Starting system	Manual / Automatic
Cooling	Air
Alternator	MARELLI

Poles	4
Fuel tank capacity (L)	100
Consumption (L/h)	127 Lt/h al 75% del carico
Running time (h)	7.87 h al 80% del carico
Length (mm)	5500
Width (mm)	2100
Height (mm)	2500
Dry weight (Kg)	8200
Silenced	Yes
Super silenced	Yes
ATS Switch device	Optional ATS
Voltage regulator	Si
Engine manufacturer	Perkins