



MOSA GE 3600 BMI GENERATOR 4 KW SUPER SILENT INVERTER STAGEV

Reference: MOSA GE 3600 BMI

MOSA GE3600BMI GENERATOR 4 KW SUPERSILENCED INVERTER STAGEV

MOSA GE3600BMI is a supersilenced single-phase generator, equipped with a GENKINS OHV 225 StageV petrol-powered engine, delivering a maximum power of 4KW, complete with **inverter voltage regulator**.

Even quieter and more efficient than traditional models, the MOSA GE3600BMI inverter genset delivers up to 4KW in single-phase mode, suitable for powering sophisticated electronic equipment that is sensitive to voltage and frequency variations. Thanks to inverter technology, it is therefore possible to quietly and easily enjoy all the little comforts of home wherever you are: lights, fans, a coffee machine, laptops, radio or TV.

The compact size and light weight make the supersilenced MOSA GE3600BMI extremely manageable and easy to transport thanks to the trolley with integrated wheels and pull-out telescopic handle, making it extremely versatile. The 12 Lt tank allows a continuous operation of more 8 hours.

The safety of use is guaranteed by overload protection and engine shutdown for low oil level. The super-silent MOSA GE3600BMI can also be used in parallel, i.e. it can be connected to another generator of the same type to deliver twice the power and increase efficiency.

The GE3600BMI is also equipped with two 230 V (16 A) domestic voltage sockets, two USB ports and a 12 V (5 A) battery charging socket to power lights, radios, TVs, small appliances, laptops and tablets, mobile phones and much more.

STAGEV EMISSIONS REGULATION

MOSA GE3600BMI equipped with "mobile" STAGEV motorization, as required by the European Regulation 2016/1628. These new engines make it possible to exponentially reduce the emissions of particulate and nitrogen oxides delivered by the generator into the environment, and guarantee a reduction in environmental impact by 200% compared to standard engines.

Technical features MOSA GE3600BMI generator:

Phase type: Single phase
Continuous use power: 4 KVA / 4 KW
Maximum power 3.6 KVA / 3.6 KW
Motor: GENKINS 225 230M
Revs : Variable 3600 rpm
Emissions standard: StageV
Starting: Recoil with wrap-around car
Fuel: Petrol
Voltage: 230 V
Frequency: 50 Hz

Socket panel: 2 x schuko 16A 230 V
 Capacit tank: 12 l
 Consumption at 75% load: 1.4 l / h
 Autonomy: 8.5 h
 Sound pressure: 66.8 dB (A) @ 7 m
 Voltage regulator: Inverter
 Length: 605 mm
 Width: 432 mm
 Height: 500 mm
 Net weight: 42 Kg

Are you looking for a generator with different technical characteristics? [HERE](#) you can find the area dedicated to Mosa generators or other specialized brands.

The images and technical data are not binding and may be subject to revisions by the manufacturer.

Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	4
Continuous power single phase (KW)	3.6
Maximum power single phase (KVA)	4
Continuous power single phase (KVA)	3.6
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230
Sockets configuration	2 x 230V 16A 2P+T SCHUKO
Engine	GK225
Emissions Regulations	Stage 5
Engine rpm (rpm)	3600
Starting system	Manual / Electric
Engine capacity (cm ³)	223
Number cylinders	1
Alternator	Permanent magnets, self-excited, brushless
Fuel tank capacity (L)	12
Consumption (L/h)	1.4
Running time (h)	8.5
Acoustic power	92 dB(A)
Acoustic pressure	66 dB(A) at 7 m
Length (mm)	605

Width (mm)	432
Height (mm)	500
Dry weight (Kg)	42
Silenced	Yes
Super silenced	Yes
Product type	Generator
ATS Switch device	No ATS
Voltage regulator	Inverter
