



CUMMINS C1675D5A Gruppo Elettrogeno Trifase 1675KVA Silenziato Diesel

Reference: C1675D5A

CUMMINS C1675D5A Three Phase Generator 1675KVA Silent Diesel

The CUMMINS C1675D5A is a powerful three-phase electric generator, designed to provide reliable and continuous power in large industrial and commercial applications. Thanks to its Cummins engine, this generator guarantees high performance and long life.

Main features:

Power: With a maximum power of 1675 kVA and a continuous power of 1500 kVA, this generator is able to power a wide range of electrical equipment, even under high load conditions.

Engine: Equipped with a robust Cummins KTA50-G8 diesel engine, synonymous with reliability and durability over time.

Voltage and frequency: It provides a voltage of 380-440 V and a frequency of 50 Hz, suitable for most industrial and commercial applications.

Dimensions and weight: With dimensions of 12192 mm x 2438 mm x 2896 mm and a dry weight of 18254 kg, this generator is of considerable size, but offers a lot of power.

Consumption: The fuel consumption is 253 liters per hour at 75% load, a value in line with the performance of the generator.

Silence: Thanks to the integrated soundproofing system, the noise level is reduced, ensuring comfortable operation.

Electric start: The electric start makes starting the generator quick and easy.

Electronic speed governor: Ensures precise regulation of frequency and voltage.

Technical features CUMMINS C1675D5A:

Phase type: Three phase

Continuous power: 1500 KVA / 1200 KW

Maximum power: 1675 KVA / 1340 KW

Engine: Cummins KTA50 GS8

Power supply: Diesel

Engine speed: 1500 rpm

Starting: Electric

Speed governor: Electronic

Voltage: 380-440 V

Frequency: 50 Hz

Consumption at 75% load: 253 l/h

Length: 12192 mm

Width: 2438 mm

Height: 2896 mm

Dry weight: 18254 kg

If you are looking for a product with different characteristics [CLICK HERE](#).

Images and technical data are not binding.

Technical Sheet

| Phase | Three phase |
|------------------------------------|-----------------|
| Maximum power three phase (KW) | 1340 |
| Continuous power three phase (KW) | 1200 |
| Maximum power three phase (KVA) | 1675 |
| Continuous power three phase (KVA) | 1500 |
| Fuel | Diesel |
| Frequency (Hz) | 50 |
| Voltage (V) | 380-440 |
| Engine rpm (rpm) | 1500 |
| Speed governor | Electronic |
| Consumption (L/h) | 253 at 75% load |
| Engine manufacturer | Cummins |