



## PRAMAC S6500 Single-phase Generator Set 5.3KW

Reference: PD482SY4001

Showing the excellence of Pramac's professional equipment, this generator consists of a robust structure with modern and economical diesel engine.  
Perfect for intensive applications, it is equipped with a control panel that allows to integrate many accessories and options for a better comfort and optimal control.

The image is purely indicative.

### Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	5.3
Continuous power single phase (KW)	4.4
Maximum power single phase (KVA)	5.9
Continuous power single phase (KVA)	4.8
Fuel	Diesel
Frequency (Hz)	50
Voltage (V)	230
Sockets configuration	
Engine	Yanmar L100N Electric, naturally aspirated
Engine rpm (rpm)	3000
Speed governor	Mechanical
Starting system	Elettrico
Engine capacity (cm <sup>3</sup> )	435
Oil capacity (L)	1.6
Cooling	Air
Poles	2