



GENSET MG 10000 S-R - GENERATOR 9.4 KVA

Reference: MG10000 S-R - COND

GENSET MG 10000 S-R SINGLE PHASE POWER GENERATOR 9,3KVA STAGE V

GENSET MG 10000 S-R Singlephase generating set with Lombardini 25LD330/2 STAGE V diesel engine, capable of delivering a maximum power of 9.3KVA complete with optional AVR voltage regulator.

The GENSET MG 10000 S-R generator set is compact and easy to use, equipped with a casing that lowers noise emissions and makes it super-silenced.

The GENSET MG 10000 S-R is a 9.3KVA single-phase diesel generator set with electric start. This generator is also available in the version with AVR voltage regulator, with automatic panel and remote control.

Thanks to its compact size and its very low weight, the GENSET MG 10000 S-R is a lightweight generator and easy to transport. The GENSET MG 10000 S-R also has a low fuel consumption: only 2.2 Lt/h at 75% load. The GENSET MG 10000 S-R generator set, thanks to the high quality and efficiency of its components, is ideal for various types of jobs: from small hobby work to large construction sites.

The GENSET MG 10000 S-R generator set is also available in a version with AVR voltage regulator, with remote control panel.

The generating set GENSET MG 10000 S-R includes:

- Voltmeter
- Hour meter
- Magnetothermal differential switch
- Emergency stop button
- Starting battery
- 1 singlephase socket CEE 32A, 230V - 50 Hz
- 1 singlephase socket CEE 16A, 230V - 50 Hz
- Protection for outputs
- Arrangement for operation in AMF/ATS or Remote control
- Central lifting hook

TECHNICAL FEATURES GENSET MG 6000 S-Y

Phase Type: SinglePhase
Maximum SinglePhase Power: 9.3KVA / 7.4 KW
Continuous SinglePhase Power: 8.3 KVA / 6.6 KW
VAC Voltage: 230 V
Frequency (Hz): 50
Starting Frame: Electric
Engine: Lombardini 25LD330/2

Emissions Standard: STAGE V
RPM: 3000
Power supply: Diesel
Fuel tank capacity: 10.5 l
Consumption @ 75 % load: 2.2 l/h
Autonomy @ 75 % load: 4.7 h
Acoustic pressure: 97 dB(A)
Length: 1000 mm
Width: 560 mm
Height: 730 mm
Net weight: 190 Kg

Are you looking for a generator with different technical characteristics? [Here](#) you can find the whole range of GENSET or other specialized brands

Images and technical data are not binding and may be subject to revision by the manufacturer.

Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	7.4
Continuous power single phase (KW)	6.6
Maximum power single phase (KVA)	9.4
Continuous power single phase (KVA)	8.3
Fuel	Diesel
Frequency (Hz)	50
Voltage (V)	230
Sockets configuration	1 x 230V 16A CEE - 1 x 230V 32A CEE
Engine	Lombardini 25LD330/2
Emissions Regulations	Stage 5
Engine rpm (rpm)	3000
Starting system	Electric
Engine capacity (cm ³)	654
Number cylinders	2
Cooling	Air
Alternator	Synchronous
Protection degree	IP23
Motor insulation class	H
Fuel tank capacity (L)	10.5
Consumption (L/h)	2.2

Running time (h)	4.77
Acoustic power	97 dB(A)
Acoustic pressure	72 dB(A) at 7 m
Length (mm)	1000
Width (mm)	560
Height (mm)	715
Dry weight (Kg)	190
Silenced	Yes
Super silenced	Yes
Product type	Generator
ATS Switch device	Optional ATS
Voltage regulator	Capacitor / AVR (optional)
Engine manufacturer	Lombardini