



MASE SILENT 8000 B/A GENERATOR 7 KVA SINGLE-PHASE STAGE V AVR

Reference: 003505

MASE SILENT 8000 B/A GENERATOR 7 KVA SINGLE-PHASE STAGE V AVR

MASE SILENT 8000 B/A is a single-phase generator equipped with a Petrol-powered Honda GX390 OHV StageV engine, capable of delivering a maximum power of 7 KVA.

The MASE SILENT 8000 B/A generator provides reliable energy for home, work and leisure environments, safely powering household appliances and other electronic devices.

The generator is easy to install and operate, just as simple are starting and stopping thanks to the clear and intuitive controls. MASE SILENT 8000 B/A is equipped with a Honda GX390 OHV StageV petrol engine. They are very reliable engines that guarantee efficient combustion and **reduced fuel consumption**, they are also equipped with a protection system that causes the engine to stop if the oil level is too low.

MASE SILENT 8000 B/A are designed for fixed applications and to satisfy every need, these generators stand out for their reliability and silence. The groups provide for electric starting and preparation for operation with an automatic control unit. The MASE SILENT 8000 B/A are equipped with a **10.5-liter tank** with a large cap that is easy to unscrew even with work gloves

MASE SILENT 8000 B/A has a completely steel structure and a large metal tank. The generator guarantees efficient and silent operation thanks to the Honda GX390 OHV StageV which allows to deliver a maximum power of 7 KVA.

STAGEV EMISSIONS REGULATION

The MASE SILENT 8000 B/A generator set is equipped with a "mobile" STAGEV motorization, as required by the 2016/1628 European Regulation. These new engines make it possible to exponentially reduce the emissions of particulate matter and nitrogen oxides delivered by the generator into the environment, and ensure a reduction in the environmental impact of 200% compared to standard engines.

The generator is supplied with:

- Automatic shutdown due to low oil level
- Built-in 12 V battery
- 1 single-phase CEE socket 230V - 16A
- 1 single-phase socket CEE 230V - 32A
- Protections for power outputs
- RCD switch
- Voltmeter
- Hour counter
- Fixed wheels and concealable handles for handling

TECHNICAL CHARACTERISTICS MASE SILENT 8000 B/A

Type of phase: Single-phase
Continuous power: 6.3 KVA / 5 KW
Maximum power: 7 KVA / 5.6 KW
VAC voltage: 230 V
Frequency (Hz): 50
Voltage regulator: AVR
Starting panel: Electric
Engine: Honda GX390
Emissions standard: Stage V
Revolutions per minute: 3000 rpm
Power supply : Petrol
Sockets panel: 1 x CEE 16A 230V / 1 x CEE 32A 230V
Tank capacity: 10.5 l
Autonomy: 3.2 h at 75% of load
Consumption: 3.3 l / h at 75% load
Acoustic pressure: 61 dB (A) @ 7 m
Length: 1059 mm
Width: 670 mm
Height: 740 mm
Net weight: 138 Kg

Are you looking for a power generator with different characteristics? [HERE](#) you can find the full range of MASE products or other brands specialized in the sector

The images and technical data are not binding and may be subject to revisions by the supplier.

Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	5.6
Continuous power single phase (KW)	5
Maximum power single phase (KVA)	7
Continuous power single phase (KVA)	6.3
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230
Sockets configuration	1 x CEE 16A 230V / 1 x CEE 32A 230V
Engine	Honda GX270, 4 tempi, OHV, aspirato naturalmente
Emissions Regulations	Stage 5
Engine rpm (rpm)	3000
Starting system	Electric
Engine capacity (cm ³)	390
Number cylinders	1
Cooling	Air

Alternator	Sincrono, autoeccitato, autoregolato, senza spazzole
Poles	2
Fuel tank capacity (L)	10.5
Consumption (L/h)	3.3 at 75% of the load
Running time (h)	3.3 at 75% of the load
Acoustic power	86 dB(A)
Acoustic pressure	61 dB(A) at 7 m
Length (mm)	1059
Width (mm)	670
Height (mm)	740
Dry weight (Kg)	138
Silenced	Yes
Super silenced	Yes
ATS Switch device	Optional ATS
Voltage regulator	AVR
Engine manufacturer	Honda