

## TECNOGEN H2700

Reference: H 5000 SS - C



### Electrogenic group TECNOGEN H5000SS 3,6 KW

Generator TECNOGEN H5000SS single-phase of 3.6 KW with Honda engine of 3000 rpm powered by gasoline. The TECNOGEN H5000SS generating set is easy to use and is small in size, easy to handle and easy to maintain. The TECNOGEN H5000SS genset is equipped with electric start.

#### Why buy a H5000SS genset?

First of all, they solve problems of lack of electricity during blackouts in different environments, from homes to businesses. The TECNOGEN H5000SS generator set is also used to provide electricity at construction sites and for hobby use. The professional generators are light machines, easy to transport, compact and robust, simple to use and with low management costs. They also present an excellent quality/price ratio.

On the TECNOGEN H5000SS generator set it is possible to install lifting hooks, very convenient to move the current generator with an overhead crane or a small crane.

#### The following are the main features:

Maximum single-phase power: 3.6 KW  
Maximum single-phase power: 4.5 KVA  
Fuel: Gasoline  
Voltage: 230 V  
Frequency: 50 Hz  
Motor: Honda GX270  
Start: Electric  
Length: 940 mm  
Width: 510 mm  
Height: 550 mm  
Weight: 106 Kg

#### All TECNOGEN range

TECNOGEN generator sets are available in both single-phase and three-phase versions, with powers from 2.3 to 21 KVA MAX, equipped with gasoline or diesel engines, air-cooled, 3000 rpm, electric start and/or manual start with recoil starter. Compact, simplified and economical, they boast an excellent price/performance/size/weight ratio. Easily transportable thanks to the reduced dimensions due to an essential equipment, they are suitable for all those who need an economic source of energy, however, assembled with first-class components that ensure absolute reliability. TECNOGEN gasoline versions of COMPACT line, thanks to the Honda engines of the latest generation, fall within the parameters of the noise directive 2000/14/EC.

Are you looking for a different model of current generator or generator set? Visit the section dedicated to [land based generators](#).

Images and technical data are not binding.

## Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	3.6
Maximum power single phase (KVA)	4.5
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230
Engine	HONDA GC160
Engine rpm (rpm)	3000
Starting system	Electric
Engine capacity (cm <sup>3</sup> )	270
Number cylinders	1
Cooling	Air
Fuel tank capacity (L)	7
Consumption (L/h)	1.5
Running time (h)	4.6
Acoustic power	88 dB(A)
Length (mm)	940
Width (mm)	510
Height (mm)	550
Dry weight (Kg)	106
Silenced	No
Super silenced	Yes
ATS Switch device	Optional ATS
Voltage regulator	No
Engine manufacturer	Honda