



TELAIR ENERGY 4010B WITH AUTOMATIC CONTROL PANEL

Reference: 05861

Super-silenced gasoline generators with Yamaha engine contained in a soundproof metal case.
 Fully automatic electronic starting system with remote control panel and 5 metres of cable equipped with: total and partial hour counter, oil and petrol level indicator light, high temperature indicator with automatic engine stop.
 Built-in battery charger 12 Volt/10A. Removable bottom drawer for easy maintenance of the generator.
 The ASP panel allows the automatic switching on and off in case the generator is connected to a battery charger (230/12 Volt) with its battery.

The images are purely indicative.

Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	3.8
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230
Engine	Yamaha MZ250
Starting system	Manual / Electric
Alternator	Synchronous
Poles	2
Consumption (L/h)	2
Acoustic pressure	60 dB(A) at 7 m
Length (mm)	665
Width (mm)	460
Height (mm)	345
Dry weight (Kg)	82
Inverter	No

AVR	No
Compound	No
Silenced	Yes
Super silenced	Yes
Product type	Generator
Voltage regulator	No
Engine manufacturer	Yamaha
