



TELAIR ENERGY 4010D WITH AUTOMATIC CONTROL PANEL

Reference: 05911

TELAIR ENERGY 4010D GENERATOR WITH AUTOMATIC CONTROL PANEL

TELAIR ENERGY 4010D vehicular generator with 3.4 KW automatic control panel is a new generation, very low fuel consumption, single-phase 230 V single-phase **supersilenced** generator with Hatz diesel engine.

Can be installed by connecting directly to the diesel vehicle's fuel tank, thus eliminating any auxiliary tanks. The TELAIR ENERGY 4010D is built with a metal container with double soundproofing that greatly reduces noise emissions. It can be provided with a completely automatic electronic starting system with remote control panel with 5 meters of cable equipped with: total and partial hours counter, engine temperature control lights, oil and gas oil level.

The automatic control panel allows the control in automatic motion of the generator simplifying the operations on the panel. The TELAIR ENERGY 4010D also has a built-in 12 V / 10 A battery charger. Removable bottom drawer for easy maintenance of the TELAIR ENERGY 4010D.

The TELAIR ENERGY 4010D has a design able to integrate itself to the perfection on every type of motorhome both in its external shape and with every particular of the inside furnishing. A continuous technical innovation fruit of a long experience, renewed and projected into the future by the enthusiasm, the fantasy and the competence of a team of young designers.

The TELAIR ENERGY 4010D is built with materials of excellent quality and subjected to various tests to ensure maximum durability. In addition, the group is contained in a metal case soundproofed with highly insulating materials, so as to further reduce the noise level and make it possible to use even when there are other vehicles in the vicinity. The sturdy metal structure is equipped with an extractable drawer that allows easy access to the generator to carry out mechanical maintenance operations in a practical and safe manner.

THE TECHNICAL CHARACTERISTICS TELAIR ENERGY 4010D

Phase Type: Single Phase
Maximum Power: 3.4 KW
Continuous Power: 3.2 KW
Voltage: 230 V
Frequency: 50 Hz
Motor: HATZ 1B30 V
Fuel: Diesel
Start: Electric
Fuel Consumption: 1.6 lt/h
Acoustic Pressure: 66 dBA @ 7m
Width: 415 mm
Length: 690 mm
Height: 391 mm
Weight: 98 Kg

Browse through our extensive catalog of [vehicular generators](#) to find the right vehicular generator for your needs like the TELAIR.

Images and technical data are not binding.

....

Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	3.4
Fuel	Diesel
Frequency (Hz)	50
Voltage (V)	230
Engine	Hatz 1B30V
Starting system	Electric
Alternator	Synchronous
Poles	2
Consumption (L/h)	0.9
Acoustic pressure	63 dB(A) at 7 m
Length (mm)	690
Width (mm)	415
Height (mm)	390
Dry weight (Kg)	98
Inverter	No
AVR	No
Compound	No
Silenced	Yes
Super silenced	Yes
Product type	Generator
Voltage regulator	No
Engine manufacturer	Hatz