



VINCO CC2500LPG Manual Generator AVR 230V/50Hz

Reference: 60170

VINCO CC2500LPG Manual Generator AVR 230V/50Hz

The VINCO CC2500LPG is a versatile and powerful generator, capable of running on three different types of fuel: petrol, LPG and natural gas. It offers a maximum power of 3.5 kW on petrol, 3.0 kW on LPG and 2.8 kW on natural gas, with nominal powers of 3.0 kW, 2.5 kW and 2.3 kW respectively.

Equipped with a 7.5 HP motor, it supplies a single-phase current at 230V/50Hz and is equipped with an AVR voltage regulator for greater stability. It has a manual start and a digital display that allows you to easily monitor the operating parameters.

It has a 16A socket and a 12V socket. With a noise level of 96 dBA, a net weight of 37 kg and compact dimensions (61x46x44 cm), the VINCO CC2500LPG is a practical and reliable solution for various energy needs.

Technical Features:

Petrol power: 3.5 kW max / 3.0 kW nominal
LPG power: 3.0 kW max / 2.5 kW nominal
Methane power: 2.8 kW max / 2.3 kW nominal
Motor power: 7.5 HP
Single phase: 230V/50Hz
Starting: Manual
Digital display: Yes
Voltage regulator: AVR
12V socket: Yes
Sockets: 1 x 16A
Noise level: 96 dBA
Net weight: 37 Kg
Product dimensions: 61x46x44 cm

If you are looking for a product with similar characteristics [CLICK HERE](#).

Technical Sheet

Phase	Single phase
Fuel	LPG

Frequency (Hz)	50
Voltage (V)	230
Sockets configuration	1 x 16A
Engine	4 Tempi
Starting system	Manuale
Cooling	Air
Acoustic pressure	96 dB(A)
AVR	Yes
Weight (Kg)	37
12V sockets	yes
Maximum petrol power	3,5 Kw Max
Continuous Petrol Power	3,0 Kw
Maximum LPG Power	3,0 Kw Max
Continuous LPG Power	2,5 Kw
Maximum Methane Power	2,8 Kw Max
Continuous Methane Power	2,3 Kw
Digital Display	yes
Product Dimensions (cm)	61x46x44