



VINCO AG-HA-6500

Reference: 67154

Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	1
Continuous power single phase (KW)	0.9
Maximum power single phase (KVA)	1.25
Continuous power single phase (KVA)	1.13
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230
Engine	4 stroke
Engine rpm (rpm)	5500
Starting system	Pull starter
Oil capacity (L)	0.5
Cooling	Air
Fuel tank capacity (L)	2.7
Consumption (L/h)	0.68
Running time (h)	4
Acoustic pressure	59 dB(A) at 7 m
Length (mm)	465
Width (mm)	285
Height (mm)	425
Dry weight (Kg)	15

Silenced	Yes
Super silenced	No
ATS Switch device	No ATS
Voltage regulator	Inverter
Engine manufacturer	Vinco
