

## VTE MOVE 12000 F

Reference: VTE MOVE 12000 F /



### VTE MOVE12000F super-silenced 10 KW vehicle generator

VTE MOVE12000F single phase 10 KW vehicle generator with Lombardini 3000 rpm diesel engine with soundproofing capsule and supersilenced. The single-phase VTE MOVE12000F vehicle generator has an electric start.

The alternator of the VTE MOVE12000F single-phase vehicle generator has permanent magnets. Thanks to its casing, the MOVE12000F vehicle generator is very quiet and has noise emissions of only 54 dB(A). Designed with high quality components it has a reduced fuel consumption: only 0.35 Lt/KW/h.

Remote control and control of the MOVE12000F single-phase vehicle generator with:

- Hour meter
- Load indicator
- Automatic stop for low oil pressure and water overtemperature
- Starter motor release
- Quick connector and 15 meters of cable

Born from the deep-rooted experience of Volpi Tecno Energia in the field of vehicle generators, MOVE is the brand dedicated to generators for vehicular, military and residential use. From 4 KW and up, the vehicle generators in this range are the quietest, most compact and lightest with the same performance. The technologies developed by Volpi Tecno Energia are able to reduce the overall dimensions to a minimum, thus ensuring a lower weight and greater efficiency of the vehicle generators that are ideal for installation on trucks, military vehicles or any other type.

These vehicle generators are the quietest: in addition, vibrations are reduced to a minimum and make generators like MOVE12000F always competitive on the market. Thanks to the production flexibility of the Trieste plant and to the technical skills developed in the sector, Volpi Tecno Energia is able to design and manufacture customized products built ad hoc according to the customer's needs.

If you are looking for another product such as the MOVE12000F vehicular generator you can consult the entire catalogue of terrestrial generators.

Images and technical data are not binding.

### Technical Sheet

Phase	Single phase
Continuous power single phase (KW)	10
Continuous power single phase (KVA)	12
Fuel	Diesel

Frequency (Hz)	50
Voltage (V)	230
Engine	Lombardini LDW1003
Engine rpm (rpm)	3000
Starting system	Electric
Number cylinders	3
Cooling	A liquido totale a circuito chiuso con radiatore esterno
Alternator	Permanent magnets
Consumption (L/h)	0.35
Acoustic pressure	54 dB(A)
Length (mm)	860
Width (mm)	580
Height (mm)	650
Dry weight (Kg)	220
Silenced	Yes
Super silenced	No
Product type	Generator
ATS Switch device	No ATS
Voltage regulator	No
Engine manufacturer	Lombardini