



MOSA GE S-7000 BBM ELECTRIC STARTER

Reference:

Gasoline generator with Briggs&Stratton engine, electric starter. Single phase power 5 KW.

Features:

- Electric Start
- Engine shut down for low oil level
- Circuit breaker
- Fuel level gauge
- Protective frame and partially covered
- Silenced
- Portable
- Meets EC directives for safety
- AVR version on request

The image is purely indicative.

Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	6
Continuous power single phase (KW)	5
Maximum power single phase (KVA)	6.7
Continuous power single phase (KVA)	5.5
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230
Sockets configuration	1 x 230V 32A 2P+T CEE - 1 x 230V 16A 2P+T CEE - 1 x 230V 16A 2P+T SCHUKO
Engine	Briggs&Stratton XR2100, 4 stroke, OHV
Engine rpm (rpm)	3000
Speed governor	Mechanical
Starting system	Elettrico

Engine capacity (cm ³)	420
Number cylinders	1
Oil capacity (L)	1.1
Cooling	Air
Alternator	Sincrono, autoeccitato, autoregolato, senza spazzole
Bore x stroke (mm)	90 x 66
Fuel tank capacity (L)	20
Consumption (L/h)	2.7 al 75% del carico
Running time (h)	10.5 at 75% of the load
Acoustic power	99 dB(A)
Acoustic pressure	74 dB(A) at 7 m
Length (mm)	770
Width (mm)	520
Height (mm)	650
Dry weight (Kg)	104
Silenced	Yes
Super silenced	No
ATS Switch device	No ATS
Voltage regulator	No
Engine manufacturer	Briggs&Stratton