



## CGM 25NG GAS METANO - APERTO CON CENTRALINA MANUALE

Reference: CGM 30GPL COFANATO MANUALE /

### Technical Sheet

Phase	Single phase / Three phase
Maximum power three phase (KW)	26.4
Continuous power three phase (KW)	24
Maximum power three phase (KVA)	33
Continuous power three phase (KVA)	30
Fuel	LPG
Frequency (Hz)	50
Voltage (V)	230 / 400
Sockets configuration	1 x 400V 63A 5P - 1 x 230V 16A 3P
Engine	General Motors RMG 3000
Engine rpm (rpm)	1500
Speed governor	Electronic
Starting system	Electric
Engine capacity (cm <sup>3</sup> )	3000
Number cylinders	4
Cylinders' position	In line
Cooling	Water
Alternator	Marelli, brushless
Poles	4
Bore x stroke (mm)	101.6 x 91.4
Consumption (L/h)	15.1 at 100% of the load

Acoustic pressure	67 dB(A) at 7 m
Length (mm)	2200
Width (mm)	1000
Height (mm)	1500
Dry weight (Kg)	920
Silenced	Yes
Super silenced	Yes
ATS Switch device	No ATS
Voltage regulator	AVR
Engine manufacturer	General Motors