



AGROWATT AWB 4-65 Tractor Generator Single Phase 26 kVA/ Three Phase 65 kVA AVR

Reference: 188295

- For outdoor applications (field and home), in case of blackouts and in areas not served by the power grid
- Supplied with multiplier kit and protection, support with 3-point attachment (patented design), electrical panel with multifunction digital display for real-time data reading (voltmeter, frequency meter, ammeter, hour meter)
- Durability over time and maximum protection (thermal-magnetic and differential)
- Warranty 24 months
- Easy packaging and storage

Non-binding images and technical data.

Technical Sheet

Phase	Single phase / Three phase
Maximum power single phase (KW)	20.8
Maximum power single phase (KVA)	26
Maximum power three phase (KW)	52
Maximum power three phase (KVA)	65
Frequency (Hz)	50
Voltage (V)	230 / 400
Sockets configuration	1 x 400V 32A 3P+N+T CEE - 1 x 230V 32A 2P+T CEE - 1 x 230V SCHUKO
Engine rpm (rpm)	1500
Protection degree	IP23
PTO speed (round/min)	400
Minimum tractor output (HP)	202
Transmission ratio	1 : 3.8
Length (mm)	1204
Width (mm)	640
Height (mm)	923

Dry weight (Kg)	335
Brushes	No
Voltage regulator	AVR
