



SINCRO FK2 MFA Single Phase Synchronous AC Alternator 12 kVA AVR

Reference: FK2 MFA J609b c25.4

SINCRO FK2 MFA ALTERNATOR 12KVA SINGLE-PHASE

Alternator SINCRO FK2 MFA single phase with a power of 12KVA, this unit has a Brush operation equipped with AVR voltage regulator.

The alternator is designed for operation at frequency 50 or 60 HZ, the possibility of working on these two frequencies makes it possible the application for any service voltage increasing its versatility, for the correct operation.

All the components that make up the SINCRO FK2 MFA alternator are subjected to a specific coating and/or impregnation process aimed at safeguarding the functionality of the generator and protecting the critical peers in the various conditions of use.

The SINCRO FK2 MFA alternators are designed to be exceptionally versatile, they are made to be suitable for all applications where an easy-to-transport power source is required.

SINCRO alternators all come equipped with voltage regulators, in the case of the FK2 MFA AVR model.

The voltage regulator is an electronic device which regulates the alternating current coming from the alternator and converts it into direct current.

In our field voltage regulators are widely used in the latest generation of synchronous generators.

All synchronous machines need an electronic control system to work, and this device, known as "voltage regulator" or "AVR" (acronym of Automatic Voltage Regulator), guarantees the good working of the machine and above all of the electric network underneath it.

Select the alternator that reflects the **technical specifications you require**, visit our [dedicated section](#) to understand how.

SINCRO FK2 MFA TECHNICAL SPECIFICATIONS

Phase Type: Single Phase
Maximum SinglePhase Output: 11.5 KW
Continuous SinglePhase Output: 9.6 KW
Maximum singlephase output: 14.4 KVA
Continuous singlephase output: 12.0 KVA
Frequency: 50-60 Hz
Voltage: 230 V
Protection class: IP23
Alternator speed: 3000 rpm
Number of poles: 2
Weight: 55.0 Kg

With Brushes
Voltage regulator: AVR
Type of alternator: constant speed

Looking for a product with different features? [Here](#) you can find the full range SINCRO and other specialized brands.

Images and technical data are not binding and subject to changes by the manufacturer

Technical Sheet

Phase	Single phase
Frequency (Hz)	50
Voltage (V)	230
Engine rpm (rpm)	3000
Poles	2
Single-phase power (KW)	12
Single-phase power (KVA)	12
Efficiency (%)	81.2
Protection degree	IP23
Dry weight (Kg)	55
Brushes	Yes
Type of alternator	Constant Speed
Voltage regulator	AVR