



## LINZ ALTERNATOR SP10S A 2 kVA 60 Hz Single-phase Brushless Alternator with Capacitor

Reference: SP10S A 60 Hz

The SP series consists of single-phase, brushless, 2-pole alternators with auxiliary winding (charged on the condenser) that ensures voltage regulation.

### CHARACTERISTICS

Compact and easy to assemble  
Possibility of vertical mounting  
Rear or top accessory panel  
High efficiency  
Gamma: Single-phase alternators  
Poles: 2  
Phases: Single-phase  
Adjustment: CONDENSER

### Technical Sheet

Phase	Single phase
Continuous power single phase (KW)	2
Continuous power single phase (KVA)	2
Frequency (Hz)	60
Voltage (V)	220
Engine rpm (rpm)	3600
Alternator	Synchronous, brushless
Poles	2
Single-phase power (KW)	1.7
Single-phase power (KVA)	1.7
Protection degree	IP21
Motor insulation class	H
Length (mm)	275
Width (mm)	200

---

Height (mm)	200
Brushes	No
Type of alternator	Constant Speed
Voltage regulator	Capacitor
Weight (Kg)	11.3

---