



LINZ SP10S D 3.7 kVA 60 Hz Single-phase Brushless Alternator with Capacitor

Reference: SP10S D 60 Hz

The SP series consists of single-phase, brushless, 2-pole alternators with auxiliary winding (charged on the condenser) that ensures voltage regulation.

CHARACTERISTICS

Compact and easy to assemble
Possibility of vertical mounting
Rear or top accessory panel
High efficiency
Gamma: Single-phase alternators
Poles: 2
Phases: Single-phase
Adjustment: CONDENSER

Technical Sheet

Phase	Single phase
Continuous power single phase (KW)	3.7
Continuous power single phase (KVA)	3.7
Frequency (Hz)	60
Voltage (V)	220
Engine rpm (rpm)	3600
Alternator	Synchronous, brushless
Poles	2
Single-phase power (KVA)	3.7
Protection degree	IP21
Motor insulation class	H
Length (mm)	275
Width (mm)	200
Height (mm)	200

Brushes	No
Type of alternator	Constant Speed
Voltage regulator	Capacitor
Weight (Kg)	16.3
