



LINZ E1C10M H Single-phase alternator 110/220V 7.25 kVA 60 Hz Brushless

Reference: E1C10M H 60 Hz

The E1C10M series consists of single-phase, brushless, 2-pole alternators with auxiliary winding (charged on the condenser) that ensures voltage regulation.

CHARACTERISTICS

- Compact and easy to assemble
- Possibility of feeding any type of load
- Wide range of accessories
- High efficiency
- Gamma: Single-phase alternators
- Poles: 2
- Phases: Single-phase
- Adjustment: CONDENSER
- Application: FLOW-UP
- Images and technical data are not binding.

Technical Sheet

Phase	Single phase
Continuous power single phase (KW)	7.2
Continuous power single phase (KVA)	7.2
Frequency (Hz)	60
Voltage (V)	110 / 220
Engine rpm (rpm)	3600
Alternator	Synchronous, brushless
Poles	2
Single-phase power (KVA)	7.2
Protection degree	IP21
Motor insulation class	H

Length (mm)	395
Width (mm)	195
Height (mm)	249
Brushes	No
Type of alternator	Constant Speed
Voltage regulator	Capacitor
Weight (Kg)	29.3
