



GENERATOR FISCHER PANDA 22-4 PMS

Reference: FP0014968

MARINE GENERATOR FISCHER PANDA 22-4PMS SUPERSILENCED 21.9 KVA

Generator for boats Fischer Panda 22-4PMS single-phase 21.9 KVA with 1500 rpm motor. The Fischer Panda 22-4PMS marine generator is designed with a soundproof cabin that makes it super-silent. The Fischer Panda 22-4PMS marine generator is built with a Kubota diesel-powered engine. The Fischer Panda 22-4PMS marine generator alternator is 4-pole with H insulation class. Thanks to its compactness, size and low weight, the Fischer Panda 22-4PMS marine generator is also perfect for installation on boats with tight spaces.

Main data of the Fischer Panda 22-4PMS generator:

Phase Type: Single-phase
Maximum Output: 18.6 kW
Continuous Output: 16.7 kW
Maximum Output: 21.9 kVA
Continuous Output: 19.7 kVA
Frequency: 50 Hz
Voltage: 230 V
Engine rpm: 1500 rpm
Displacement: 2434 cc.
Cooling: Water
Sound Cover Type: GFK (Glass fibre reinforced polyester)
Sound pressure: 53 dB(A) at 7 m
Length: 1255 mm
Width: 515 mm
Height: 670 mm
Dry weight: 315 Kg

Based on the rugged Fischer Panda 22-4PMS generator set, these heavy duty (HD) versions operate at 1500 rpm / 50Hz. The Fischer Panda 22-4PMS generator is enclosed in a super quiet soundproofed capsule. The generators are heavier than standard PMS generators. They use a heavy-duty diesel engine and because they run at 1500 rpm, they have a 4-wire coil, which also means that the alternator has a heavier 4-pole construction. The heavy-duty construction and low rpm results in a durable and quiet generator set.

Generators AC 50 Hz / 1500 rpm (PMS-HD)

Heavy Duty (HD) at 1500 rpm. Based on this robust nautical generator set, these heavy duty versions are enclosed in a super quiet soundproofed capsule.

If you are looking for a marine generator set like the Fischer Panda 22-4PMS but with different technical features then you can browse the entire [marine generator](#) catalogue.

Images and technical data are not binding.

Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	18.6
Continuous power single phase (KW)	16.7
Maximum power single phase (KVA)	21.9
Continuous power single phase (KVA)	19.7
Fuel	Diesel
Frequency (Hz)	50
Voltage (V)	230
Engine	Kubota V2403M
Engine rpm (rpm)	1500
Speed governor	Electronic
Starting system	Elettrico
Engine capacity (cm ³)	2434
Number cylinders	4
Cooling	Water
Poles	4
Motor insulation class	H
Length (mm)	1255
Width (mm)	720
Height (mm)	770
Dry weight (Kg)	350
Silenced	Yes
Super silenced	Yes
Product type	Generator
Voltage regulator	Capacitor
Engine manufacturer	Kubota