



## GREEN POWER GP11A-PW OPEN

Reference: 00370

The GREEN POWER 1500 rpm generators are designed for versatile use, from construction sites to industry, from agriculture to civil protection.

Robust welded steel frames with built-in tank of variable capacity produced by Green Power, engines and alternators supplied by the most important manufacturers in the sector and cutting-edge control units are the elements to ensure generators of excellent quality.

The hoods are made of steel, which allows them to be used in tropical environments. The Green Power covers guarantee maximum accessibility for maintenance and cleaning operations.

Green Power's strong point is the design and implementation within the company, a feature that helps to reduce the time to market of the product and allows any customization.

### You can choose between the versions:

- Open group with Compound-Liz alternator (automatic power pack)
- Open group with AVR-Leroy alternator (automatic power pack)
- Open group with AVR-Mecc Alte alternator (automatic power pack)
- Open group with AVR-Stamford alternator (automatic power pack)

The image is purely indicative.

### Technical Sheet

Phase	Three phase
Maximum power three phase (KW)	8
Continuous power three phase (KW)	7.2
Maximum power three phase (KVA)	10
Continuous power three phase (KVA)	9
Fuel	Diesel
Frequency (Hz)	50
Voltage (V)	230 / 400
Sockets configuration	1 x 400V 16A 3P+T CEE - 1 x 230V 16A 2P+T CEE - 1 x 230V 16A

SCHUKO

Engine	Perkins 403A-11G1
Emissions Regulations	NON EMISSIONATO
Engine rpm (rpm)	1500
Speed governor	Mechanical
Starting system	Elettrico
Engine capacity (cm <sup>3</sup> )	1131
Number cylinders	3
Cylinders' position	In line
Cooling	Water
Alternator	Linz E1S13SB/4, synchronous, with brushes
Poles	4
Protection degree	IP21
Fuel tank capacity (L)	55
Consumption (L/h)	2.3 al 75% del carico
Running time (h)	23 al 75% del carico
Length (mm)	1300
Width (mm)	700
Height (mm)	1000
Dry weight (Kg)	360
Silenced	No
Super silenced	No
ATS Switch device	Optional ATS
Voltage regulator	Compound / AVR (optional)